



---

# VRX-58L

## Audio/Video Receiver 5.8 GHz

---

This is the most sensitive and definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver works with any TV system and it has 8 selectable channels and a special Video inverse function.



Technical Specifications	
BATTERY POWERED	9-12 V
CURRENT CONSUMPTION	395 mA
DEMODULATION	WFM
SENSITIVITY	-86 dBm
ANTENNA CONNECTOR	SMA
VIDEO INVERSE FUNCTION	YES
VIDEO OUTPUT	1V
AUDIO OUTPUT	300 mV
POLARITY PROTECTED	YES
PLL (PHASE LOOKED LOOP)	YES
TEMPERATURE RANGE:	-20+70°C
NUMBER OF CHANNELS	8 CHANNELS IN 5.7 GHz- 5.8 GHz BAND
DIMENSIONS	4.7" X 3" X1"