



VRX-58S AUDIO/VIDEO RECEIVER 5.8 GHz



This small receiver is definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver has 8 channels in 5.8 GHz band.

Technical Specifications	
Operating Frequencies:	5750-5850 MHz
Channel settings:	Dip-switches
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Minimum required voltage:	9 V
Battery power:	12 V
Video distortion:	3%
Video Format:	PAL, NTSC
Current Consumption:	250 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Audio output:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-10 +65 °C
Dimensions:	4.3" X 2.8 " X 1.0"
Weight:	100 grams
Demodulation:	WFM