



RMX -2000 RECEIVER 900-2000 MHz WITH DIGITAL DISPLAY

RMX-200 is the most sensitive digitally controlled receiver for 900 -2000 MHz. Fully synthesized this receiver has an SMA connector. The frequency is easy to control from the front panel in 125 kHz step with two up/down buttons. There are thousands of available channels in the range 900 -2000 MHz



Technical Specifications	
Operating Frequencies:	900-2000 MHz
Channel step	125 kHz
Battery power:	12 V
Video output:	1 V
Video Format:	NTSC or PAL
Current Consumption:	380 mA
Sensitivity:	-83dBm
Dimension :	6"x4"x2"