



VRX-24LTS

Audio/Video Receiver 2.4 GHz

The newest receiver VRX 24 LTS is the most sensitive receiver with a tunable function to access any frequency in 2.4 GHz - 2.5 GHz band. This receiver has built-in a special AFT (Automatic frequency tuning) control function. Receiver VRX 24LTS is a very low power unit. It is easy to use and works from 7 V- 14 V DC power / 200 mA! This receiver works for any TV system.



| Technical Specifications | |
|---|--|
| Operating Frequencies: | Tunable frequencies in 2.3- 2.5 GHz band |
| Channel: | Any |
| DC Voltage: | 9 V- 12 V |
| RF power: | N/A |
| Minimum required voltage: | 9 V |
| Battery power: | 12 V/ 300 mA |
| Video distortion: | 3% |
| Sensitivity: | -92 dBm |
| Video Format: | PAL, NTSC |
| Current Consumption: | 280 mA / 9 V |
| Antenna: | Recommended high gain, omni directional ant. |
| Antenna Connector: | SMA |
| Impedance: | 50 ohms |
| Video output Connector: | RCA F |
| Video Impedance: | 75 ohms |
| Audio outputs: | RCA 300 mV |
| Carrier frequencies for audio channels: | 6 MHz and 6.5 MHz |
| Temperature Range: | -20 +70* C |
| Dimensions: | 4.5" X 2.8 " X 1.7" |
| Weight: | 120 grams |