



---

# R-810

## Audio/Video Receiver 2.4 GHz with LCD display

---

The newest receiver R-810 is the most sensitive receiver with LCD display for 2.4 GHz -2.5 GHz band. It is easy to use and works from [6 V- 12 V DC power / 500 mA](#)! This small TV set has direct Video/Audio outputs and an SMA antenna connector.



Technical Specifications	
Operating Frequencies:	2300 MHz- 2500 MHz
Channel:	#4
DC Voltage:	6 V- 12 V
Sensitivity:	-75 dBm
Minimum required voltage:	6 V
Battery power:	6 - 12 V/ 500 mA
Video distortion:	3%
Sensitivity:	-92 dBm
Video Format:	PAL, NTSC
Current Consumption:	500 mA / 9 V
Antenna:	Recommended high gain, omni directional ant.
Antenna Connector:	SMA (Optional)
Impedance:	50 ohms
Video output Connector:	Mini
Video Impedance:	75 ohms
Audio output:	300 mV
Carrier frequencies for audio channels:	6 MHz
Temperature Range:	-5 +50* C
Dimensions:	6" X 4" X 0.8"
Weight:	150 grams
Demodulation:	WFM