



RMX -2000 RECEIVER 1600-2000 MHz WITH DIGITAL DISPLAY

RMX-200 is the most sensitive digitally controlled receiver for 1.6 GHz - 2 GHz. Fully synthesized this receiver has an SMA connector. The frequency is easy to control from the front panel in 125 kHz step with two up/down buttons. There are thousands of available channels in the range 1.6 GHz - 2.0 GHz..



Technical Specifications	
Operating Frequencies:	1600-2000 MHz
Channel step	125 kHz
Battery power:	12 V
Video output:	1 V
Video Format:	NTSC or PAL
Current Consumption:	380 mA
Sensitivity:	-83dBm
Dimension :	6"X4"X2"