

RF-links.com is introducing the smallest professional PLL sound transmitter. Implementing newest RF technology, the S-900 delivers 50mW of RF power.



The new S-900 module is made for professionals to revolutionize wireless functionality for "size-conscious" applications in theater, television and film. The S-900 is fully synthesized transmitter with an audio input 100 mV and includes lower self-noise, and an easily programmable channels. One 9 V battery will deliver six hours of continuous operation. The S-900 is the latest addition of PLL wireless modules and implements Motorola's programmable synthesizer. In theatrical and film applications, sound designers and engineers are forever pushing for smaller, unobtrusive transmitters. The S-900 fulfills their needs while enhancing overall performance.

Model numbers: **S-700** (700 MHz module) **S-900** (900 MHz module)

Features: S-700

5 CHANNELS	CURRENT CONSUMPTION 50 mA
POWER SUPPLY 7-12 V	FREQUENCY RANGE 690 MHz- 750 MHz
DEVIATION 5 kHz- 100 kHz	PROCESSOR CRYSTAL FREQUENCY 24 MHz
RF POWER 50 mW	FREQUENCY STABILITY 0.005%
PLL CONTROLLED	MODULATION NARROW or WIDEBAND FM
AUDIO INPUT 100 mV	AUDIO FREQUENCY RESPONSE 30 Hz- 16 kHz

RF-LINKS.COM , RPO 60043, 1032 Pape Ave , Toronto , ON , M4K 3Z3

Copyright © 2000-2003, Vs LC. All rights reserved.