



VRX-58S

Audio/Video Receiver

5.8 GHz

This small receiver is definitely the best 5.8 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 5.8 GHz. This receiver has 8 channels in 5.8 GHz band.



Technical Specifications	
Operating Frequencies:	5650-5900 MHz
Channel:	Channels from 1-8
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Maximum range:	N/A
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	N/A
Antenna Connector:	SMA
Impedance:	50 ohms
Audio outputs:	300 mV
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-10 +65 °C
Dimensions:	4.3" X 2.8" X 1.0"
Weight:	100 grams
Demodulation:	WFM