



VRX-1700 Audio/Video Receiver 1700 MHz

This is the most sensitive and definitely the best 1.7 GHz Audio/ Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas 1.7 GHz. It has 8 selectable channels. This receiver works with any TV system.



AUDIO 1 AUDIO 2 VIDEO POWER

ANTENNA

Technical Specifications	
Operating Frequencies:	1700 MHz- 1900 MHz
Channel:	#1, 2, 3, 4, 5, 6, 7, 8
DC Voltage:	9 V- 12 V
RF power:	N/A
Minimum required voltage:	9 V
Battery power:	12 V/ 300 mA
Video distortion:	3%
Sensitivity:	-89 dBm
Video Format:	PAL, NTSC
Current Consumption:	280 mA / 9 V
Antenna:	Recommended high gain, omni directional ant.
Antenna Connector:	SMA
Impedance:	50 ohms
Video output Connector:	RCA F
Video Impedance:	75 ohms
Two Audio outputs:	300 mV per channel
Carrier frequencies for audio channels:	6 MHz and 6.5 MHz
Temperature Range:	-25 +65* C
Dimensions:	2.5" X 5.7" X 0.8"
Weight:	200 grams
Demodulation:	WFM