

VRX-4900L

Audio/Video Receiver 4.9 GHz

This small receiver is definitely the best 4.9 GHz Video receiver on the market. Fully synthesized this receiver has an SMA connector for different type of antennas for 4.9 GHz. This receiver has 8 channels and it covers all frequencies in 4.9 GHz band. This small video receiver can access any video transmitter in 4.9 GHz band.



Audio on request.

Technical Specifications	
Operating Frequency:	4900 MHz
Channels:	4 channels (8 channels on request)
DC Voltage:	9 V – 12 V
Sensitivity:	-86 dBm
Minimum required voltage:	10 V
Battery power:	12 V
Video distortion:	3%
Audio carriers:	6 MHz, 6.5 MHz
Video Format:	PAL, NTSC
Current Consumption:	350 mA / 12 V
Antenna:	High-gain recommended
Antenna Connector:	SMA
Impedance:	50 ohms
Audio input:	300 mV (on request only)
Video/Audio Connectors:	RCA F
Video Impedance:	75 ohms
Video level:	1 V
Temperature Range:	-40 +78 °C
Dimensions:	2.5" X 1.5 " X 0.75"
Weight:	100 grams
Demodulation:	WFM