



VRX-58C Audio/Video Receiver 5.8 GHz

This is a special video receiver for **5.8 GHz** with excellent sensitivity and easy to use. It is fully synthesized and built in a professional metal box. This receiver has 8 channels selectable from the front panel. The receiver will work from **10 V- 14 V DC**. Video out is 1 V / 75 ohm. This receiver has stereo audio portion carriers 6 and 6.5 MHz. This receiver complies with all FCC standards! High gain antenna can be connected via an SMA connector for the best performances and range.

8 CHANNELS ARE AVAILABLE IN 5.8 GHz RANGE. The combination of 3 switches on the front panel can make 8 channels in 5.8 GHz band.



Technical Specifications	
POWER SUPPLY	10 V- 14.4 V
CURRENT CONSUMPTION	380 mA
DEMODULATION	WFM
SENSITIVITY	-86 dBm
ANTENNA CONNECTOR	SMA
VIDEO INVERSE FUNCTION	N/A
VIDEO OUTPUT	1V
AUDIO OUTPUT	300 mV
POLARITY PROTECTED	YES
PLL (PHASE LOCKED LOOP)	YES
TEMPERATURE RANGE:	-20+70°C
NUMBER OF CHANNELS	FULL RANGE TUNABLE
DIMENSIONS	6.5" X 4" X 2.1"