



AXD-69/H DIGITAL TV AMPLIFIER UHF TV CHANNELS CH 14-CH 69



This digital TV amplifier is an excellent broadcast solution for small TV stations, monitoring or experiments. It is fully synthesized and broadband for UHF channels 14-69. Power output is over 10 W / 50 ohms. Required power input is 0 dBm that makes it a great solution for the most digital exciters available on the market.

RF Technical Specifications	
VISION SPECIFICATIONS	
RF OUTPUT	10 W
OUTPUT IMPEDANCE:	50 ohm
Antenna Connector:	BNC /N F
Return loss	<1.25
Input power	0 dBm
Frequency:	471-868 MHz