



---

# DCV-900 Tunable Audio/Video Receiver For 900 MHz

---

The newest AM (amplitude modulation) receiver for 900 MHz Model DCV 900 is definitely the smallest and the best receiver of it's kind. This receiver is extremely stable, with frequency tunable function and excellent picture quality. This receiver works from 9 V- 12 V / 180 mA DC. Antenna connector is a BNC type and it is possible to use different kind of antennas with gain.



Technical Specifications	
BATTERY POWERED	9 V - 12 V
VIDEO OUTPUT	1V
CURRENT CONSUMPTION	180 mA
AUDIO OUTPUT	300 mV
FREQUENCY DEMODULATION	AM
TV SYSTEMS	NTSC
SENSITIVITY	-92 dBm
TUNABLE BAND	902- 928 MHz
ANTENNA CONNECTOR	SMA
DIMENSIONS	3.0" X 1.0" X 2.1"
VIDEO/AUDIO OUTPUTS	RCA
IF FREQUENCY	45 MHz